

Introduction

The JKT is the perfect tool for checking and tuning PA systems along with various pieces of equipment. Phantom powered, it has one combined input/output XLR and one combined XLR and 1/4" jack output. The JKT delivers a full range of tones from 20Hz through to 30kHz, as well as both White and Pink Noise.

Features

- Phantom power supply
- Multiple, low impedance outputs: XLR, XLR + Jack 1/4"
- Sine wave generator 20Hz to 30kHz
- Pink noise generator
- White noise generator
- Output level



Application

Specifically designed as an engineer's Tone Generator solution tool for checking and tuning PA systems

- Live performance
- Fixed installations
- Portable

Signal Output	
Output Channels	Jack 1/4", 2x XLR
Output Impedance	50Ω line / 600Ω monitor
Features	
Level Control	-∞ to 0dB
Indicators	Power-ON LED
Tone generator	20Hz to 30kHz
White noise generator	YES
Pink noise generator	YES

Power	
Phantom Power	48 to 56V / 8mA
Cabinet	
Cabinet Material	Heavy duty metal
Physical Dimensions	
Height	40 mm (1.57")
Width	80 mm (3.15")
Depth	131 mm (5.16")
Weight	630 g (1.39lbs)

The future of sound. Made perfectly clear.



KV2 Audio International, Nádražní 936, Milevsko 399 01, Czech Republic
Tel.: +420 383 809 320
Email: info@kv2audio.com | Web: www.kv2audio.com